

EW-7208APC

安装指南

09-2014 / v1.0

Edimax Technology Co., Ltd.

No.3, Wu-Chuan 3rd Road, Wu-Gu, New Taipei City 24891, Taiwan

Email: support@edimax.com.tw

Edimax Technology Europe B.V.

Fijenhof 2, 5652 AE Eindhoven, The Netherlands

Email: support@edimax.nl

Edimax Computer Company

3350 Scott Blvd., Bldg.15 Santa Clara, CA 95054, USA

Live Tech Support: 1(800) 652-6776


Email: support@edimax.com

包装内容

请先检查包装内容物



EW-7208APC



天线 x 3



CD 光盘片



网络线




安装指南




电源变压器

安装


1. 请先将天线旋入产品本体后方的天线接头。请注意，2.4GHz 和 5GHz 天线需安装在正确对应的位置(2.4GHz 天线装在两侧，5GHz 天线装在中间，如背板印刷指示)



2. 接上电源



3. 请确认产品本体后方的无线开/关切换键已切换至 On(开启)的位置，同时 power, 2.4GHz 及 5GHz 的 LED 指示灯为亮灯状态。



4. 请启用智能型装置的无线 Wi-Fi，选择无线网络名称为 "edimax.setup" 或 "edimax.setup5G" 的无线网络，并与其连接。


 使用手机或平板设定的用户，操作系统需为 iOS 4(或以上版本) 或 Android 4(或以上版本)

5. 启动浏览器，您会被自动导引至如下" 开始" 画面，若无，请您在网址列输入 ***http://edimax.setup*** 以进入" 开始" 画面，接着请点击" 开始" 。



 若您无法进入 ***http://edimax.setup*** 的开始画面，请先确认您的无线上网装置的联机方式是设定为浮动式 IP (Dynamic IP)，如您需要进一步说明，请参考使用手册说明。

6. 视您所需的网络环境应用，选择您希望 EW-7208APC 的应用模式—AP 模式(默认)或其他模式



不同网络模式设定按这里！

按下去！
开始设定您的无线网络


EW-7208APC 具备五种网络环境应用模式，各模式说明如下：

Access Point Mode 无线基地台模式	在一个有线网络环境中，您的无线手机或平板电脑并没有无线网络可供联机；或者是您家中使用的无线速度与覆盖范围都不是太好，此时，您确实有需要建立一个新的无线网络环境。 除了上面描述的环境，其实还有许多的无线网络布署与建置，都可以用「无线基地台」模式来解决。
Range Extender Mode 无线讯号延伸器模式	在一个既定的 2.4GHz 或 5GHz 的无线网络环境中，难免会有一些无线讯号的死角，您需要延伸既定的无线讯号至这些死角。此环境请使用「无线讯号延伸器」模式来解决。
Wireless Bridge Mode 无线网桥模式	现实生活中，有非常多的产品都只是有线网络设备(如数字家电音响、游戏机)，当您买这些装置产品时，您可能会想，若把它们接家里的有线局域网络时，要怎么接？要不是


	得把网络线拉长一些；再不就是将有线网络装置放在网络线会经过的位置。 「无线网桥」模式可以解决这个困扰，可以把全部的有线网络装置摇身变成无线网络装置，在不需要网络线的情形下，让您将有线网络装置想放在哪就放在哪，而且一次至少可以接四台有线网络装置。
Wi-Fi Router Mode 无线路由器模式	当您有申请电信公司(如：中华电信光世代/远传大宽带/台湾大宽带)或有线电视公司的Internet 服务(如：凯擘大宽带)，您需要分享给更多网络设备使用有线或无线方式联机Internet，此环境请使用「无线路由器」模式。
WISP Mode 无线公共热点模式	如果您居住的城市有提供无线因特网服务热点；或是您在超商、连锁咖啡店或旅游饭店内，希望透过他们提供的无线热点，来达到超过两个以上的网络设备 (例如：您有智能型手机与笔电都要上网)联机Internet 的时候。您可以使用「无线公共热点」模式让更多人使用更多设备联机Internet。

7. 请依循画面指示完成设定。如需更多说明，请参考使用说明。

无线基地台模式(Wi-Fi Access Point):



其他模式:




网页式设定界面

完成设定后，您即可登入本产品的网页式设定界面做进一步设定配置或变更设定。请开启浏览器，在网址列中输入 <http://edimax.setup> 并与其联机




若您无法登入 **edimax.setup** 网页式设定界面，请以网络线连接本产品和您的电脑后，再试一次。

看到如下画面出现时，请输入出厂默认用户名称 “admin” 及密码 “1234” 。



接着，您会进入“ 状态(Status)” 页(如下图示)，请利用左侧选单导引您进入各功能选项设定，如您需要更进一步说明，请参考使用手册。



疑难解答

1. 在无线讯号延伸模式下，EW-7208APC 是否可以延伸 2.4GHz 和 5GHz 的无线讯号？

- a. 是的！EW-7208APC 可同步延伸 2.4GHz 和 5GHz 的无线讯号，只是您必须在执行 iQSetup 时，设定好 EW-7208APC 要连接延伸的 2.4GHz 和 5GHz 无线网络，也就是在 iQSetup 执行当中，您会被要求选择要延伸讯号的 2.4GHz 和 5GHz 无线网络，并输入各别的新 SSID 及联机该 2.4GHz 和 5GHz 无线网络的密码。



当然，在执行 *iQSetup* 时，您也可以选择关闭 2.4GHz 或 5GHz 无线网络（如无适当联机的无线网络或您并不想要使用的时候），只要您关闭 2.4GHz 或 5GHz 任一无线网络，属于该频段的无线上网装置，将无法连接至您的 EW-7208APC。

2. 在无线讯号延伸模式下，EW-7208APC 是双频无线讯号延伸器，如果此时将它以有线的方式与上网装置连接会如何？

- a. 当您将上网装置以网络线连接处于无线讯号延伸器模式下的 EW-7208APC，EW-7208APC 默认联机的无线网络会是 5GHz 无线网络，但若无 5GHz 网络时，EW-7208APC 会自动连接至 2.4GHz 网络。

3. 我如何在“无线讯号延伸器模式(range extender mode)下，连接到一隐藏网络？

- a. 请在 iQSetup 安装精灵执行时，手动输入该隐藏网络的 2.4GHz 及(或) 5GHz SSID(网络名称)，及该隐藏网络 2.4GHz 和 5GHz 无线网络的联机密码。


Range Extender

2.4GHz Wireless Site Survey

Please set a new Wi-Fi network name (SSID) for the range extender if you wish, and set the security key for your existing wireless network if required.

Wi-Fi network name (SSID):


Range extender SSID:
Encryption: Disable

Back
Next

Wi-Fi network name	输入您要联机的隐藏网络的名称
Range extender SSID	为您的 EW-7208APC 取一个与上层网络名称 (SSID) 一致且易于辨识的名称，如上层网络名称(SSID) 的命名是"Edimax_Router"，则您的 EW-7208APC 无线路由器可命名为 "Edimax_Router_2EX"
Encryption	输入该隐藏网络的联机密码

4. EW-7208APC 的 LED 指示灯各代表甚么的意义？

本产品底座印有 LED 指示灯号说明图示



LED 名称	灯色	灯号状态	灯号说明
电源 	白灯	灯亮	EW-7208APC 电源已启动
		灯熄	EW-7208APC 电源已关闭
网际网路 	蓝灯	灯亮	已联机至网际网路
		灯号闪烁	出厂默认状态或网络线未插上或未联机至网际网路
2.4GHz 无线网络 	蓝灯	灯亮	2.4GHz 无线网络数据正在传输或接收中
		灯号闪烁	2.4GHz 无线网络 WPS 功能启动
		灯熄	2.4GHz 无线网络未有数据传输或接收
5GHz 无线网络 	蓝灯	灯亮	5GHz 无线网络数据正在传输或接收中
		灯号闪烁	5GHz 无线网络 WPS 功能启动
		灯熄	5GHz 无线网络未有数据传输或接收

5. 我无法联机 Internet?

- 请确认所有线材已正确连接或换一条网络线。
- 请确认您是否可以登入网页式设定界面，如不行，请再确认您的电脑是否设定为动态 IP 地址 (Dynamic IP Address)。至于如何确认是否为浮动式 IP 地址，请参考 CD 内附使用手册。
- 登入网页式设定界面后，请前往网际网路> 网际网路设定页，确认联机类型正确。若您不确定您的因特网类型为何，请与您的网际网路服务提供商 (即 ISP 业者)联系。
- 请将您的电脑直接连接至您家的数据机，试看您是否能联机至网际网路，如果不行，请与您的 ISP 业者或 EDIMAX 客服人员请求协助。

6. 我无法登入网页式设定界面?

- a. 请确认您的电脑网络卡是否设定为动态 IP 地址 (Dynamic IP Address)。
关于如何确认是否为动态 IP 地址, 请参考 CD 内附使用手册。

7. 如何将本产品恢复至出厂默认值?

- a. 要将本产品恢复至出厂默认值, 您必须长按产品本体后方的 WPS/Reset 按键(至少 10 秒钟)直到电源 LED 指示灯转为快闪状态, 再静待约 1 分钟让产品完成重新启动, 所有设定都将恢复至出厂预设状态, 您可在产品本体后方的卷标上找到出厂默认数据(如下图标)



登入无线基地台	在浏览器网址列输入 <i>http://edimax.setup</i> 执行 iQ Setup 或进阶设定。请注意, 您必须使用无线或有线方式连接至本产品。
用户名称/密码	出厂默认的用户名称及密码是 admin/1234, 在您登入网页设定接口时, 会被要求输入。
无线网络名称	这是本产品的出厂默认网络名称(SSID)。如欲登入网页设定接口 <i>http://edimax.setup</i> , 请您先连接至此 SSID
MAC 地址	MAC 地址是用以辨识网络中的装置, 就像装置的身分证一样, 每个装置的 MAC 地址皆不同, 本产品的 MAC 标示在产品底面的卷

	标贴纸上。
PIN 码	这是设定 WPS 快速联机时需要的 PIN 码

8. 忘记密码

- 请将路由器恢复成出厂预设状态(使用预设的使用者名称“admin”和默认密码“1234”。如上图所示，在产品的底部卷标上显示出厂默认数据)。

9. 在无线讯号延伸模式下，我的 EW-7208APC 讯号很弱？

讯号弱通常起因于其他装置的干扰或障碍物的阻隔：

- 请将产品远离其他会产生无线电波的产品(如微波炉或无线电话等)
- 请勿将此产品放置于房间角落或靠近金属/被金属包覆。
- 请让本产品和您的无线上网装置之间，阻隔或障碍物越少越好。

在无线讯号延伸模式下，本产品的无线讯号可能因为您的无线路由器讯号不佳而转弱，所以帮您的无线路由器和本产品选择一个最佳位置是很重要的。如何挑选本产品的最佳位置？建议您将本产品放置在无线路由器和您的装置须要上网地点的中间，若将本产品放置在距离无线路由器过远的地方，则可能造成本产品抓取不到上层的无线讯号产生没有讯号可以延伸。

10. 当本产品处在不同模式下时，WAN 端口和 LAN 埠作用一样吗？

不一样的！WAN 端口和 LAN 端口的作用在不同模式下会有些许不同。

- 在**无线基地台模式**下，WAN 端口并无作用。您家的路由器是连接到本产品的其中一个 LAN 埠，而剩下的 LAN 埠则可供有在线网终端设备连接。
- 在**无线讯号延伸器模式**下，WAN 端口也无作用，而 LAN 埠也同样是供有在线网终端设备连接。
- 在**无线桥接模式**下，WAN 端口是没有作用的，而所有的 LAN 埠是提供给有线网络装置使用。
- 在**无线路由器模式**下，本产品的 WAN 端口是直接连接您家的 xDSL 数据机，而 LAN 端口则是以网络线连接您的有在线网终端设备(如电脑)。
- 在**WISP 模式**下，WAN 端口是没有作用的，而所有的 LAN 埠是提供给有线网络装置使用。

Federal Communication Commission Interference Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

1. Reorient or relocate the receiving antenna.
2. Increase the separation between the equipment and receiver.
3. Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
4. Consult the dealer or an experienced radio technician for help.

FCC Caution

This device and its antenna must not be co-located or operating in conjunction with any other antenna or transmitter. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Any changes or modifications not expressly approved by the party responsible for compliance could void the authority to operate equipment.

Federal Communications Commission (FCC) Radiation Exposure Statement

This equipment complies with FCC radiation exposure set forth for an uncontrolled environment. In order to avoid the possibility of exceeding the FCC radio frequency exposure limits, human proximity to the antenna shall not be less than 2.5cm (1 inch) during normal operation.

Federal Communications Commission (FCC) RF Exposure Requirements

This EUT is compliance with SAR for general population/uncontrolled exposure limits in ANSI/IEEE C95.1-1999 and had been tested in accordance with the measurement methods and procedures specified in OET Bulletin 65 Supplement C. The equipment version marketed in US is restricted to usage of the channels 1-11 only. This equipment is restricted to *indoor* use when operated in the 5.15 to 5.25 GHz frequency range.

R&TTE Compliance Statement

This equipment complies with all the requirements of DIRECTIVE 1999/5/EC OF THE EUROPEAN PARLIAMENT AND THE COUNCIL of March 9, 1999 on radio equipment and telecommunication terminal equipment and the mutual recognition of their conformity (R&TTE). The R&TTE Directive repeals and replaces in the directive 98/13/EEC (Telecommunications Terminal Equipment and Satellite Earth Station Equipment) As of April 8, 2000.

Safety

This equipment is designed with the utmost care for the safety of those who install and use it. However, special attention must be paid to the dangers of electric shock and static electricity when working with electrical equipment. All guidelines of this and of the computer manufacture must therefore be allowed at all times to ensure the safe use of the equipment.

EU Countries Intended for Use

The ETSI version of this device is intended for home and office use in Austria, Belgium, Bulgaria, Cyprus, Czech, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, Netherlands, Poland, Portugal, Romania, Slovakia, Slovenia, Spain, Sweden, Turkey, and United Kingdom. The ETSI version of this device is also authorized for use in EFTA member states: Iceland, Liechtenstein, Norway, and Switzerland.

EU Countries Not Intended for Use

None

EU Declaration of Conformity

English:	This equipment is in compliance with the essential requirements and other relevant provisions of Directive 1999/5/EC, 2009/125/EC.
Français:	Cet équipement est conforme aux exigences essentielles et autres dispositions de la directive 1999/5/CE, 2009/125/CE.
Čeština:	Toto zařízení je v souladu se základními požadavky a ostatními příslušnými ustanoveními směrnic 1999/5/ES, 2009/125/ES.
Polski:	Urządzenie jest zgodne z ogólnymi wymaganiami oraz szczególnymi warunkami określonymi Dyrektywą UE 1999/5/EC, 2009/125/EC.
Română:	Acest echipament este în conformitate cu cerințele esențiale și alte prevederi relevante ale Directivei 1999/5/CE, 2009/125/CE.
Русский:	Это оборудование соответствует основным требованиям и положениям Директивы 1999/5/EC, 2009/125/EC.
Magyar:	Ez a berendezés megfelel az alapvető követelményeknek és más vonatkozó irányelveknek (1999/5/EK, 2009/125/EC).
Türkçe:	Bu cihaz 1999/5/EC, 2009/125/EC direktifleri zorunlu istekler ve diğer hükümlerle ile uyumludur.
Українська:	Обладнання відповідає вимогам і умовам директиви 1999/5/EC, 2009/125/EC.
Slovenčina:	Toto zariadenie spĺňa základné požiadavky a ďalšie príslušné ustanovenia smerníc 1999/5/ES, 2009/125/ES.
Deutsch:	Dieses Gerät erfüllt die Voraussetzungen gemäß den Richtlinien 1999/5/EC, 2009/125/EC.
Español:	El presente equipo cumple los requisitos esenciales de la Directiva 1999/5/EC, 2009/125/EC.
Italiano:	Questo apparecchio è conforme ai requisiti essenziali e alle altre disposizioni applicabili della Direttiva 1999/5/CE, 2009/125/CE.
Nederlands:	Dit apparaat voldoet aan de essentiële eisen en andere van toepassing zijnde bepalingen van richtlijn 1999/5/EC, 2009/125/EC.
Português:	Este equipamento cumpre os requisitos essenciais da Directiva 1999/5/EC, 2009/125/EC.
Norsk:	Dette utstyret er i samsvar med de viktigste kravene og andre relevante regler i Direktiv 1999/5/EC, 2009/125/EC.
Svenska:	Denna utrustning är i överensstämmelse med de väsentliga kraven och övriga relevanta bestämmelser i direktiv 1999/5/EG, 2009/125/EG.
Dansk:	Dette udstyr er i overensstemmelse med de væsentligste krav og andre relevante forordninger i direktiv 1999/5/EC, 2009/125/EC.
Suomi:	Tämä laite täyttää direktiivien 1999/5/EY, 2009/125/EY oleelliset vaatimukset ja muut asiaankuuluvat määräykset.

FOR USE IN          
            
                

WEEE Directive & Product Disposal



At the end of its serviceable life, this product should not be treated as household or general waste. It should be handed over to the applicable collection point for the recycling of electrical and electronic equipment, or returned to the supplier for disposal.

Declaration of Conformity

We, Edimax Technology Co., Ltd., declare under our sole responsibility, that the equipment described below complies with the requirements of the European R&TTE directives.

Equipment: AC750 Multi-Function Dual-Band Wi-Fi Access Point
Model No.: EW-7208APC

The following European standards for essential requirements have been followed:

Directives 1999/5/EC

Spectrum : ETSI EN 300 328 V1.8.1 (2012-06);
ETSI EN 301 893 V1.7.1 (2012-06)
EMC : EN 301 489-1 V1.9.2 (2011-09);
EN 301 489-17 V2.2.1 (2012-09);
Safety (LVD) : IEC 60950-1:2005 (2nd Edition);Am 1:2009
EN 60950-1:2006+A11:2009+A1:2010+A12:2011

Recommendation 1999/5/EC

EMF : EN 62311:2008

Directives 2006/95/EC

Safety (LVD) : IEC 60950-1:2005 (2nd Edition);Am 1:2009
EN 60950-1:2006+A11:2009+A1:2010+A12:2011

Edimax Technology Co., Ltd.
No. 3, Wu Chuan 3rd Road,
Wu-Ku Industrial Park,
New Taipei City, Taiwan



Date of Signature: September, 2014

Signature:

Printed Name:

Albert Chang

Title:

Director

Edimax Technology Co., Ltd.

Notice According to GNU General Public License Version 2

This product includes software that is subject to the GNU General Public License version 2. The program is free software and distributed without any warranty of the author. We offer, valid for at least three years, to give you, for a charge no more than the costs of physically performing source distribution, a complete machine-readable copy of the corresponding source code.

Das Produkt beinhaltet Software, die den Bedingungen der GNU/GPL-Version 2 unterliegt. Das Programm ist eine sog. „Free Software“, der Autor stellt das Programm ohne irgendeine Gewährleistungen zur Verfügung. Wir bieten Ihnen für einen Zeitraum von drei Jahren an, eine vollständige maschinenlesbare Kopie des Quelltextes der Programme zur Verfügung zu stellen – zu nicht höheren Kosten als denen, die durch den physikalischen Kopiervorgang anfallen.

GNU GENERAL PUBLIC LICENSE

Version 2, June 1991

Copyright (C) 1989, 1991 Free Software Foundation, Inc. 51 Franklin Street, Fifth Floor, Boston, MA 02110-1301, USA
Everyone is permitted to copy and distribute verbatim copies of this license document, but changing it is not allowed.

Preamble

The licenses for most software are designed to take away your freedom to share and change it. By contrast, the GNU General Public License is intended to guarantee your freedom to share and change free software--to make sure the software is free for all its users. This General Public License applies to most of the Free Software Foundation's software and to any other program whose authors commit to using it. (Some other Free Software Foundation software is covered by the GNU Lesser General Public License instead.) You can apply it to your programs, too.

When we speak of free software, we are referring to freedom, not price. Our General Public Licenses are designed to make sure that you have the freedom to distribute copies of free software (and charge for this service if you wish), that you receive source code or can get it if you want it, that you can change the software or use pieces of it in new free programs; and that you know you can do these things.

To protect your rights, we need to make restrictions that forbid anyone to deny you these rights or to ask you to surrender the rights. These restrictions translate to certain responsibilities for you if you distribute copies of the software, or if you modify it.

For example, if you distribute copies of such a program, whether gratis or for a fee, you must give the recipients all the rights that you have. You must make sure that they, too, receive or can get the source code. And you must show them these terms so they know their rights.

We protect your rights with two steps: (1) copyright the software, and (2) offer you this license which gives you legal permission to copy, distribute and/or modify the software.

Also, for each author's protection and ours, we want to make certain that everyone understands that there is no warranty for this free software. If the software is modified by someone else and passed on, we want its recipients to know that what they have is not the original, so that any problems introduced by others will not reflect on the original authors' reputations.

Finally, any free program is threatened constantly by software patents. We wish to avoid the danger that redistributors of a free program will individually obtain patent licenses, in effect making the program proprietary. To prevent this, we have made it clear that any patent must be licensed for everyone's free use or not licensed at all.

The precise terms and conditions for copying, distribution and modification follow.

TERMS AND CONDITIONS FOR COPYING, DISTRIBUTION AND MODIFICATION

0. This License applies to any program or other work which contains a notice placed by the copyright holder saying it may be distributed under the terms of this General Public License. The "Program", below, refers to any such program or work, and a "work based on the Program" means either the Program or any derivative work under copyright law: that is to say, a work containing the Program or a portion of it, either verbatim or with modifications and/or translated into another language. (Hereinafter, translation is included without limitation in the term "modification".) Each licensee is addressed as "you".

Activities other than copying, distribution and modification are not covered by this License; they are outside its scope. The act of running the Program is not restricted, and the output from the Program is covered only if its contents constitute a work based on the Program (independent of having been made by running the Program). Whether that is true depends on what the Program does.

1. You may copy and distribute verbatim copies of the Program's source code as you receive it, in any medium, provided that you conspicuously and appropriately publish on each copy an appropriate copyright notice and disclaimer of warranty; keep

intact all the notices that refer to this License and to the absence of any warranty; and give any other recipients of the Program a copy of this License along with the Program.

You may charge a fee for the physical act of transferring a copy, and you may at your option offer warranty protection in exchange for a fee.

2. You may modify your copy or copies of the Program or any portion of it, thus forming a work based on the Program, and copy and distribute such modifications or work under the terms of Section 1 above, provided that you also meet all of these conditions:

- a) You must cause the modified files to carry prominent notices stating that you changed the files and the date of any change.
- b) You must cause any work that you distribute or publish, that in whole or in part contains or is derived from the Program or any part thereof, to be licensed as a whole at no charge to all third parties under the terms of this License.
- c) If the modified program normally reads commands interactively when run, you must cause it, when started running for such interactive use in the most ordinary way, to print or display an announcement including an appropriate copyright notice and a notice that there is no warranty (or else, saying that you provide a warranty) and that users may redistribute the program under these conditions, and telling the user how to view a copy of this License. (Exception: if the Program itself is interactive but does not normally print such an announcement, your work based on the Program is not required to print an announcement.)

These requirements apply to the modified work as a whole. If identifiable sections of that work are not derived from the Program, and can be reasonably considered independent and separate works in themselves, then this License, and its terms, do not apply to those sections when you distribute them as separate works. But when you distribute the same sections as part of a whole which is a work based on the Program, the distribution of the whole must be on the terms of this License, whose permissions for other licensees extend to the entire whole, and thus to each and every part regardless of who wrote it.

Thus, it is not the intent of this section to claim rights or contest your rights to work written entirely by you; rather, the intent is to exercise the right to control the distribution of derivative or collective works based on the Program.

In addition, mere aggregation of another work not based on the Program with the Program (or with a work based on the Program) on a volume of a storage or distribution medium does not bring the other work under the scope of this License.

3. You may copy and distribute the Program (or a work based on it, under Section 2) in object code or executable form under the terms of Sections 1 and 2 above provided that you also do one of the following:

- a) Accompany it with the complete corresponding machine-readable source code, which must be distributed under the terms of Sections 1 and 2 above on a medium customarily used for software interchange; or,
- b) Accompany it with a written offer, valid for at least three years, to give any third party, for a charge no more than your cost of physically performing source distribution, a complete machine-readable copy of the corresponding source code, to be distributed under the terms of Sections 1 and 2 above on a medium customarily used for software interchange; or,
- c) Accompany it with the information you received as to the offer to distribute corresponding source code. (This alternative is allowed only for noncommercial distribution and only if you received the program in object code or executable form with such an offer, in accord with Subsection b above.)

The source code for a work means the preferred form of the work for making modifications to it. For an executable work, complete source code means all the source code for all modules it contains, plus any associated interface definition files, plus the scripts used to control compilation and installation of the executable. However, as a special exception, the source code distributed need not include anything that is normally distributed (in either source or binary form) with the major components (compiler, kernel, and so on) of the operating system on which the executable runs, unless that component itself accompanies the executable.

If distribution of executable or object code is made by offering access to copy from a designated place, then offering equivalent access to copy the source code from the same place counts as distribution of the source code, even though third parties are not compelled to copy the source along with the object code.

4. You may not copy, modify, sublicense, or distribute the Program except as expressly provided under this License. Any attempt otherwise to copy, modify, sublicense or distribute the Program is void, and will automatically terminate your rights under this License. However, parties who have received copies, or rights, from you under this License will not have their licenses terminated so long as such parties remain in full compliance.

5. You are not required to accept this License, since you have not signed it. However, nothing else grants you permission to modify or distribute the Program or its derivative works. These actions are prohibited by law if you do not accept this License. Therefore, by modifying or distributing the Program (or any work based on the Program), you indicate your acceptance of this License to do so, and all its terms and conditions for copying, distributing or modifying the Program or works based on it.

6. Each time you redistribute the Program (or any work based on the Program), the recipient automatically receives a license from the original licensor to copy, distribute or modify the Program subject to these terms and conditions. You may not impose any further restrictions on the recipients' exercise of the rights granted herein. You are not responsible for enforcing compliance by third parties to this License.

7. If, as a consequence of a court judgment or allegation of patent infringement or for any other reason (not limited to patent issues), conditions are imposed on you (whether by court order, agreement or otherwise) that contradict the conditions of this License, they do not excuse you from the conditions of this License. If you cannot distribute so as to satisfy simultaneously your obligations under this License and any other pertinent obligations, then as a consequence you may not distribute the Program at all. For example, if a patent license would not permit royalty-free redistribution of the Program by all those who receive copies directly or indirectly through you, then the only way you could satisfy both it and this License would be to refrain entirely from distribution of the Program.

If any portion of this section is held invalid or unenforceable under any particular circumstance, the balance of the section is intended to apply and the section as a whole is intended to apply in other circumstances.

It is not the purpose of this section to induce you to infringe any patents or other property right claims or to contest validity of any such claims; this section has the sole purpose of protecting the integrity of the free software distribution system, which is implemented by public license practices. Many people have made generous contributions to the wide range of software distributed through that system in reliance on consistent application of that system; it is up to the author/donor to decide if he or she is willing to distribute software through any other system and a licensee cannot impose that choice.

This section is intended to make thoroughly clear what is believed to be a consequence of the rest of this License.

8. If the distribution and/or use of the Program is restricted in certain countries either by patents or by copyrighted interfaces, the original copyright holder who places the Program under this License may add an explicit geographical distribution limitation excluding those countries, so that distribution is permitted only in or among countries not thus excluded. In such case, this License incorporates the limitation as if written in the body of this License.

9. The Free Software Foundation may publish revised and/or new versions of the General Public License from time to time. Such new versions will be similar in spirit to the present version, but may differ in detail to address new problems or concerns.

Each version is given a distinguishing version number. If the Program specifies a version number of this License which applies to it and "any later version", you have the option of following the terms and conditions either of that version or of any later version published by the Free Software Foundation. If the Program does not specify a version number of this License, you may choose any version ever published by the Free Software Foundation.

10. If you wish to incorporate parts of the Program into other free programs whose distribution conditions are different, write to the author to ask for permission. For software which is copyrighted by the Free Software Foundation, write to the Free Software Foundation; we sometimes make exceptions for this. Our decision will be guided by the two goals of preserving the free status of all derivatives of our free software and of promoting the sharing and reuse of software generally.

NO WARRANTY

11. BECAUSE THE PROGRAM IS LICENSED FREE OF CHARGE, THERE IS NO WARRANTY FOR THE PROGRAM, TO THE EXTENT PERMITTED BY APPLICABLE LAW. EXCEPT WHEN OTHERWISE STATED IN WRITING THE COPYRIGHT HOLDERS AND/OR OTHER PARTIES PROVIDE THE PROGRAM "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. THE ENTIRE RISK AS TO THE QUALITY AND PERFORMANCE OF THE PROGRAM IS WITH YOU. SHOULD THE PROGRAM PROVE DEFECTIVE, YOU ASSUME THE COST OF ALL NECESSARY SERVICING, REPAIR OR CORRECTION.

12. IN NO EVENT UNLESS REQUIRED BY APPLICABLE LAW OR AGREED TO IN WRITING WILL ANY COPYRIGHT HOLDER, OR ANY OTHER PARTY WHO MAY MODIFY AND/OR REDISTRIBUTE THE PROGRAM AS PERMITTED ABOVE, BE LIABLE TO YOU FOR DAMAGES, INCLUDING ANY GENERAL, SPECIAL, INCIDENTAL OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OR INABILITY TO USE THE PROGRAM (INCLUDING BUT NOT LIMITED TO LOSS OF DATA OR DATA BEING RENDERED INACCURATE OR LOSSES SUSTAINED BY YOU OR THIRD PARTIES OR A FAILURE OF THE PROGRAM TO OPERATE WITH ANY OTHER PROGRAMS), EVEN IF SUCH HOLDER OR OTHER PARTY HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

